



## ***Liaison™ Internet Router 3.0.5 Release Notes***

***July 8, 1993***

The following important information does not appear in the *Liaison Internet Router User's Guide*. We urge you to read it carefully in conjunction with the Liaison manual. If you have questions, consult the online help system or call Farallon Technical Support at (510) 814-5000.

### ***Important instructions for 68040 users with non-Apple video cards***

Installing Liaison without proper precautions may cause your computer to freeze and require you to reinstall your system software.

Please follow the instructions in the "Work-around" section below if **both** of the following conditions are true:

- You are installing Liaison on a Macintosh Quadra 800, Quadra 950, or Centris 650.
- You have a non-Apple video card installed on your computer, for example, a RasterOps Procolor 32 or SuperMac Thunder8 video card.

### ***Work-around***

To install Liaison under the circumstances described above, follow these steps:

1. Temporarily remove the video card and driver software from the computer on which you will be installing Liaison so that the computer is using the built-in video driver.
2. Copy Liaison to the Extensions folder of your System Folder.
3. Select Liaison in the Chooser, enter your serial number, and configure Liaison.
4. Shut down the Macintosh.
5. Reinstall the video card and accompanying software that you want to use.
6. Restart your Macintosh.

### ***Liaison and the Macintosh Duo***

Liaison doesn't work on a Macintosh Duo that is not in its dock. On a docked Duo, Liaison works well as an EtherTalk-to-LocalTalk router with or without an external modem. Out of the dock, you can't have both LocalTalk and Modem dial-up selected because this configuration causes the computer to hang at startup.

To configure Liaison on an undocked Duo with an external modem:

1. Open the Chooser and switch AppleTalk off.
2. Open Liaison Preferences and select only Modem Dial-up.
3. Restart your Duo. You can then use Liaison to dial out.

### ***Liaison and the Express modem***

Liaison does not currently work with the Express Modem.

### ***Installing Liaison 3.0.5***

If you are installing Liaison for the first time, follow the instructions in Chapter 3 of the *Liaison Internet Router User's Guide*. If you are upgrading Liaison 2.0.x or you are updating Liaison 3.0.x, follow the instructions below.

1. Open the Chooser and select Liaison.
2. Click the Configure pop-up menu and choose About Liaison.
3. Write down the Liaison serial number that is displayed; you will need to enter it into Liaison 3.0.5.
4. Close the Chooser.
5. Open your System Folder and drag the old Liaison file to the Trash.  
**Do not drag the Liaison Prep file to the Trash.**
6. Close the System Folder.
7. Drag the new Liaison file from the update disk to your System Folder.
8. Open the Chooser and select Liaison again. Liaison asks you to specify your default configuration information.
9. Click OK. Liaison prompts you for the serial number.
10. Type the serial number and click the Network button.
11. Enter your configuration preferences and network zone information.

Your old Liaison Prep file will retain all Address Book entries and Authorized User information but no zone or configuration information.

### ***Installing Liaisonet™***

If you are installing Liaisonet for the first time, follow the instructions in Chapter 3 of the *Liaison Internet Router User's Guide*. If you are upgrading Liaisonet 2.0.x or you are updating Liaisonet 3.0.x, follow the instructions above. Your old Liaisonet Prep file will retain all Address Book entries but no configuration information.

### ***New features in 3.0.5***

Liaison now includes greater compatibility with the following software and devices:

- Macintosh System 7.1
- SCSI devices
- AppleTalk versions later than 56
- Microsoft Mail Backup

In addition, Liaison now installs AppleTalk version 58. This allows PowerBook users running Liaison to use the Sleep command in the Special menu.

## **Revision history**

### **New features in 3.0.4**

- Supports AppleTalk versions 57.0.4 and 58
- Improved security with System 7 dialog boxes
- Increased interoperability with NetAtlas

### **Bugs fixed in 3.0.4**

- Liaison previously caused the Apple Responder to report system software version numbers incorrectly to network troubleshooting products such as NetAtlas or CheckNet. This problem has been corrected.
- When configuring extended cables, Liaison previously failed to route if you entered zero as a network number. The problem has been corrected as follows: Liaison 3.0.4 will autoconfigure if you enter zero as a network number.

### **New features in 3.0.3**

- Automatic support of mixed AppleTalk Phase I and Phase II networks
- CCL scripting for more flexible modem support
- Routing between as many as five AppleTalk networks

## **Correction to manual**

Please make the following change to page 44 of the *Liaison Internet Router User's Guide*:

Under "Creating zones on a single extended cable," step 2 says:

2. In the Preferences dialog box, select EtherTalk2 and Null Network, and then click Save.

Change this to:

2. In the Preferences dialog box, select EtherTalk2 and then click Save.

## **To obtain Liaison Technical Support**

You can reach Farallon Technical Support by calling (510) 814-5000 or faxing your questions to (510) 814-5023. Farallon also maintains a series of forums on various online network services, including AppleLink, CompuServe, Internet, and America Online.