

USB to Serial Adapter User's Guide

The 2 Serial/Geo ports provide a simple and reliable way to connect Macintosh serial devices to the new Mac generation. Serial/Geo converters are intelligent, stackable expansion modules that connect to your Mac USB port.

• Features:

1. Provides 2 Serial/Geo ports to your new Macintosh.
2. Serial port supports data transfer rates at an internal rate of 230.4kbps and with an external clocking system at a rate of 860kbps.

• Requirements:

1. iMac or other USB-equipped Macintosh with an available USB port
2. USB driver update 1.0.1 (or later)
3. Mac OS 8.1 (or later) with iMac update 1.0 (or later)

• Package:

1. Adapter: USB A type male cable to 2 Serial ports.
2. Software disc.
3. This User's Guide.

• Software Installation

Please Confirm the hardware installation was completed.

1. Double click on the “ **USB to Serial Adapter**” icon and follow the prompts..
2. Plug the Serial cable of devices into your *Adapter*.
3. Plug the USB A type into your USB computer.
4. Open **Control Panel**, choose the **iDock Setup**, you will see “Geo1”, “Geo2” ports in *Adapter* Setup Window.

Note: The list in the windows upper part contains all available ports on the *Adapter*, except for the USB ports. The USB ports on the *Adapter* are handled transparently, as with any other USB Hub, and do not need to be configured in any way. If several *Adapter* are connected to a single Macintosh, the serial and parallel ports from all

hubs appear in the list.

5. Rename the ports. Select **Port 1**, click the Port Type pop-up menu to change it to **Printer Port**. Then Select **Port 2**, click the Port type pop-up menu to change it to **Modem Port**.
6. Now your *USB to Serial Adapter* is ready for use.

Note: You can rename the ports like objects in Finder list views, by clicking on their names and typing new names. Renaming may make the ports easier to identify. You can choose how each port appears to the Macintosh by clicking n the port and choosing a type from the Port Type pop-up menu in the lower part of the window.

Compatible List

Printer: Apple Style Writer II Apple Style Writer1500 Apple Style Writer1200 Apple Style Writer2400 Apple Style Writer2500 ColorStyle WriterPro ColorStyle Writer 2200 ColorStyle Writer 4500 HP Desk Writer 550C HP Desk Writer 694C HP Desk Writer 600 HP Desk Writer 850 HP Desk Writer 870CSE EPSON PM-770C Apple Laser Writer 300	Digital Camera: Fuji DS20 Camera Olympus D200 Zoom Digital Camera Olympus D300 Zoom Digital Camera Olympus D400 Zoom Digital Camera Olympus 500 Zoom Digital Camera Olympus C-800L Digital Camera Olympus C-9000 Zoom Epson D-340L Kodak DC-50 Casio QV-10V	Others: External Modem(Zoom Tornado) Palm Pilot Professional(Us Robotic) Newton 2000 Wacom Tablet Fischertechnik Construcion Kits NON-Professional MIDI IBM Work PAD Japanese Ver. NEC AT/ATERML T45 NEC AT/ATERML W60 CASIO QV-10 ISDN IRISPen
---	---	---

However, New Motion is constantly testing new devices and adding them to the compatibility list which is listed on our website:

www.newmotion.com.tw

Please visit our website for upgraded compatibility list.



©1999 New Motion Co., Ltd. All rights reserved.